

NEW PRODUCT RELEASE



Dimensions : 12 1/8" W x 14 1/8" H x 4 1/8" D

Signs

Exits

Flexit

LED Exit Combo

Description

The Flexit Series LED exit signs with incandescent emergency light lamp head and can also be purchased without LED exit signs. Suitable for all interior applications. The construction is designed so the emergency lighting units will remain attractive and functional with minimal maintenance requirements. Best quality, durable, eye catching and UL approved.

Construction

- Low profile • Injection-molded thermoplastic housing • Scratch resistant • Textured finish
- Innovative, snap-together design allows for fast installation • Standard package includes two red or green exit faces, thermoplastic backplate and mounting bracket for single and double face
- Directional arrow knockouts for choice of direction • Test switch and charge rate indicator provided • Supplied standard with two fully adjustable glare-free lighting heads • Underwriters Laboratories, Inc. 924 listed

Electrical

- Universal 120/277 dual voltage operation
- Only 11 watt energy consumption • Emergency battery charges fully in 24 hours • Long-life LEDs offer 20 years continual-use life span • Battery maintains at least 87 1/2 percent of the normal voltage of battery and DC lamp maintains at least 60 percent of initial emergency illumination for 1 1/2 hours • Universal input short circuit and automatic reset (no fuse breaker required to protect DC lamp heads)

Mounting

- Universal mounting • Canopy kit for wall, ceiling and end mounting

Catalog Number	Universal Mounting	
L305-GRN-LEM	GREEN LETTERS	EMERGENCY HALOGEN MODULE
L305-RED-LEM	RED LETTERS	EMERGENCY HALOGEN MODULE
LEM-305		EMERGENCY HALOGEN MODULE ONLY

How to Specify : Select catalog number with desired features.

WARRANTY
FIVE YEAR TOTAL CUSTOMER SATISFACTION

Cole Lighting LED Exit Sign is guaranteed to our customers' complete satisfaction for a period of five years from date of invoice. This guarantee covers any defect in manufacturing, provided the defect develops under normal and proper use. Our guarantee liability extends only to replacement of the defective part. No labor charges for correction of the defect by repair or replacement will be honored by Cole Lighting unless prior written approval has been granted by Cole Lighting.



C. W. Cole & Company, Inc.
2560 N. Rosemead Boulevard
South El Monte, CA 91733-1593

Fax (626) 443-9253
Tel. (626) 443-2473
info@colelighting.com
www.colelighting.com